



Supervised zone loop. Max 25 detectors and plus max 25 manual call points

Cable for zone and sounder:
THW 2 x 1.0mm
Max. length 300m

Supervised sounder circuit. Max 5 bells or max 0.5A load on each loop

A supervised relay on the equipment that is controlled by FACP, e.g. fan or pump

A relay contact for fault alarm output, e.g. to drive a fault lamp

- M Manual call point
- S Smoke detector
- H Heat detector
- Ω End of line 4.7kΩ
- B Bell

	FACP configuration						
GST model	101	102	104	108/4	108/8	116/4	116/16
Total zone	1	2	4	8	8	16	16
Total sounder	2	2	2	4	8	4	16
Alarm output	no	no	no	1	1	1	1
Fault output	no	no	no	1	1	1	1
Repeater	no	no	yes	yes	yes	yes	yes